

Amendments to the Claims:

1. (Currently amended) A method of interpolating image positions in an original image to produce an interpolated output image, wherein the original image is represented by digital input pixel data, comprising the steps of:

- (a) providing a first filter having a sharp interpolation characteristic;
- (b) providing a second filter having a smooth interpolation characteristic;
- (c) interpolating a selected image position in the image using the first filter to generate a sharp interpolation output value;
- (d) interpolating a selected image position in the image using the second filter to generate a smooth interpolation output value;
- (e) calculating a different weighting coefficient for the output of each filter by estimating the image high frequency level at the selected image positions and calculating the weighting coefficients based on the estimated image high frequency level; and
- (f) selectively combining the output values from the filters as a function of the weighting coefficients, to generate an interpolation output value for the selected image position of an interpolated output image.

2. (Canceled)

3. (Currently amended) The method of claim 1 2, wherein the weighting coefficient α for the first filter output is calculated according to the relation:

$$\alpha = \min(1, \max(0, (\varphi - T_1)/(T_2 - T_1)))$$

wherein φ is the image high frequency level estimated for the given interpolation position, T_1 and T_2 are two pre-determined threshold values where $T_2 > T_1 \geq 0$; and ~~whereby that~~

_____ the weighting coefficient for the second filter output is $(1 - \alpha)$.

4. (Currently amended) The method of claim 1, wherein the interpolation output value q for the selected image position is according to the relation:

$$q = r * \alpha + s * (1 - \alpha)$$

wherein α and $(1 - \alpha)$ are the weighting coefficients for the first and second filters, respectively ($0 \leq \alpha \leq 1$), and r and s are the filter output values from the first and second filters, respectively.

5. (Original) The method of claim 1, wherein:

the first filter comprises a polyphase filter; and

the second filter comprises a polyphase filter.

6. (Original) The method of claim 5, wherein:

the first filter comprises a one dimensional FIR polyphase filter; and

the second filter comprises a one dimensional FIR polyphase filter.

7. (Original) The method of claim 5, wherein the two polyphase filters have the same length.

8. (Original) The method of claim 5, wherein each of the polyphase filters comprises a N -tap M -phase polyphase filter.

9. (Original) The method of claim 8, wherein for arbitrary or variable interpolation ratios, M has a value of 10 or larger.

10. (Original) The method of claim 8, wherein N can be either an odd or an even number value.

11. (Original) The method of claim 5, wherein the two filters are low-pass filters, such that the first filter has a sharp frequency transition band and the second filter has a smooth frequency transition band.

12. (Original) The method of claim 8, wherein:
calculating the weighting coefficient for each of the two filters further includes the steps of: estimating the image high frequency level at the selected image position, and calculating a weighting coefficient for the output of the filter based on the estimated image high frequency level; and

the image high frequency level at the selected image position is estimated based on the image high frequency components measured at original image pixels neighboring the selected image position.

13. (Original) The method of claim 12, wherein the image high frequency component at the original image pixels is measured using a high-pass filtering process.

14. (Original) The method of claim 13, wherein the image high frequency component at the original image pixels is measured using a high-pass FIR filter.

15. (Currently amended) ~~The method of claim 13,~~ A method of interpolating image positions in an original image to produce an interpolated output image, wherein the original image is represented by digital input pixel data, comprising the steps of:

_____ providing a first filter having a sharp interpolation characteristic;

_____ providing a second filter having a smooth interpolation characteristic;

_____ each of the filters comprises a N -tap M -phase polyphase filter;

_____ interpolating a selected image position in the image using the first filter to generate a sharp interpolation output value;

_____ interpolating a selected image position in the image using the second filter to generate a smooth interpolation output value;

_____ calculating a weighting coefficient for the output of each filter by estimating the image high frequency level at the selected image position based on image high frequency components measured at original image pixels neighboring the selected image position,

and calculating the weighting coefficients based on the estimated image high frequency level;

_____ selectively combining the output values from the filters as a function of the weighting coefficients, to generate an interpolation output value for the selected image position of an interpolated output image;

_____ wherein the image high frequency component ϕ_i at each of the original image pixels is measured according to the relation

$$\phi_i = |p_i - 0.5 * (p_{i-1} + p_{i+1})|$$

wherein p_i is original image pixel value where image high frequency component is to be measured, and p_{i-1} and p_{i+1} are original image pixel values of the its neighboring pixels.

16. (Original) The method of claim 15, wherein the image high frequency level ϕ at the selected image position is estimated according to the relation:

$$\phi = \sum_{i=-\frac{N}{2}+1}^{\frac{N}{2}} (0.5 * (f_{-i+1}^j + g_{-i+1}^j) * \phi_i)$$

wherein ϕ_i , $i = -\frac{N}{2} + 1, \dots, 0, \dots, \frac{N}{2}$ are the image high frequency components calculated at the original image pixels that are within the filtering range of interpolation to the selected image position, f_i^j and g_i^j are filter coefficients of sub-filters f^j and g^j for the first filter and the second filter, respectively, and j is the interpolation phase for the selected image position.

17. (Original) The method of claim 12, wherein the image high frequency level at the selected image position is estimated based on the image high frequency components calculated at two original image pixels closest to the selected image position.

18. (Currently amended) ~~The method of claim 17,~~ A method of interpolating image positions in an original image to produce an interpolated output image, wherein the original image is represented by digital input pixel data, comprising the steps of:

_____ providing a first filter having a sharp interpolation characteristic;

_____ providing a second filter having a smooth interpolation characteristic;

_____ each of the filters comprises a N -tap M -phase polyphase filter;

_____ interpolating a selected image position in the image using the first filter to generate a sharp interpolation output value;

_____ interpolating a selected image position in the image using the second filter to generate a smooth interpolation output value;

_____ calculating a weighting coefficient for the output of each filter by estimating the image high frequency level at the selected image position based on image high frequency components measured at original image pixels neighboring the selected image position, and calculating the weighting coefficients based on the estimated image high frequency level;

_____ selectively combining the output values from the filters as a function of the weighting coefficients, to generate an interpolation output value for the selected image position of an interpolated output image;

_____ wherein the image high frequency level φ at the selected image position is estimated according to the relation:

$$\varphi = d_1 * \phi_0 + d_0 * \phi_1$$

wherein ϕ_0 and ϕ_1 are the image high frequency components calculated at the two closest original image pixels, d_0 and d_1 are the distances between the selected interpolation position and the two closest original image pixel and the distance between two neighboring original image pixels is assumed to be 1, such that $d_0 + d_1 = 1$.

19. (Original) The method of claim 12, wherein the image high frequency level at the selected image position is estimated based on the image high frequency component measured at original image pixels that are within the filtering range of interpolation to the selected image position.

20. (Currently amended) ~~The method of claim 19,~~ A method of interpolating image positions in an original image to produce an interpolated output image, wherein the original image is represented by digital input pixel data, comprising the steps of:

_____ providing a first filter having a sharp interpolation characteristic;

_____ providing a second filter having a smooth interpolation characteristic;

_____ each of the filters comprises a N -tap M -phase polyphase filter;

interpolating a selected image position in the image using the first filter to
generate a sharp interpolation output value;
interpolating a selected image position in the image using the second filter to
generate a smooth interpolation output value;
calculating a weighting coefficient for the output of each filter by estimating the
image high frequency level at the selected image position based on image high frequency
components measured at original image pixels neighboring the selected image position,
and calculating the weighting coefficients based on the estimated image high frequency
level;
selectively combining the output values from the filters as a function of the
weighting coefficients, to generate an interpolation output value for the selected image
position of an interpolated output image; and
_____ wherein the image high frequency level ϕ at the selected image position is
estimated according to the relation:

$$\phi = \sum_{i=-\frac{N}{2}+1}^{\frac{N}{2}} (0.5 * (f_{-i+1}^j + g_{-i+1}^j) * \phi_i)$$

wherein ϕ_i , $i = -\frac{N}{2} + 1, \dots, 0, \dots, \frac{N}{2}$ are the image high frequency

components calculated at the original image pixels that are within the filtering range of
interpolation to the selected image position, f_i^j and g_i^j are the filter coefficients of sub-
filters f^j and g^j for the first filter and the second filter, respectively, and j is the
interpolation phase for the selected image position.

21. (Currently amended) An interpolation system that interpolates image positions in an original image to produce an interpolated output image, wherein the original image is represented by digital input pixel data, comprising:

(a) a first filter having a sharp interpolation characteristic, the first filter interpolating a selected image position in the image to generate a sharp interpolation output value;

(b) a second filter having a smooth interpolation characteristic, the second filter interpolating the selected image position in the image to generate a smooth interpolation output value;

(c) a controller that calculates a weighting coefficient for the output of each filter by estimating the image high frequency level at the selected image position, and calculating a weighting coefficient for the output of the filter based on the estimated image high frequency level; and

(d) a combiner that selectively combines the output values from the filters as a function of the weighting coefficients, to generate an interpolation output value for the selected image position of an interpolated output image.

22. (Canceled)

23. (Currently amended) The system of claim 21 ~~22~~, wherein the controller calculates the weighting coefficient α for the first filter output according to the relation:

$$\alpha = \min(1, \max(0, (\varphi - T_1)/(T_2 - T_1)))$$

wherein φ is the image high frequency level estimated for the given interpolation position, T_1 and T_2 are two pre-determined threshold values where $T_2 > T_1 \geq 0$, whereby that the weighting coefficient for the second filter output is $(1 - \alpha)$.

24. (Currently amended) The system of claim 21 22, wherein the combiner determines the interpolation output value q for the selected image position according to the relation:

$$q = r * \alpha + s * (1 - \alpha)$$

wherein α and $(1 - \alpha)$ are the weighting coefficients for the first and second filters, respectively ($0 \leq \alpha \leq 1$), and r and s are the filter output values from the first and second filters, respectively.

25. (Original) The system of claim 21, wherein:

the first filter comprises a polyphase filter; and

the second filter comprises a polyphase filter.

26. (Original) The system of claim 25, wherein:

the first filter comprises a one dimensional FIR polyphase filter; and

the second filter comprises a one dimensional FIR polyphase filter.

27. (Original) The system of claim 25, wherein the two polyphase filters have the same length.

28. (Original) The system of claim 25, wherein each of the polyphase filters comprises a N -tap M -phase polyphase filter.

29. (Original) The system of claim 28, wherein for arbitrary or variable interpolation ratios, M has a value of 10 or larger.

30. (Original) The system of claim 28, wherein N can be either an odd or an even number value.

31. (Original) The system of claim 25, wherein each of the two filters comprises a low-pass filter, such that the first filter has a sharp frequency transition band and the second filter has a smooth frequency transition band.

32. (Original) The system of claim 28, wherein:
the controller calculates the weighting coefficient for each of the two filters by estimating the image high frequency level at the selected image position, and calculating a weighting coefficient for the output of the filter based on the estimated image high frequency level, such that the image high frequency level at the selected image position is estimated based on the image high frequency components measured at original image pixels neighboring the selected image position.

33. (Original) The system of claim 32, wherein the image high frequency component at the original image pixels is measured using a high-pass filtering process.

34. (Original) The system of claim 33, wherein the image high frequency component at the original image pixels is measured using a high-pass FIR filter.

35. (Currently amended) ~~The system of claim 33,~~ An interpolation system that interpolates image positions in an original image to produce an interpolated output image, wherein the original image is represented by digital input pixel data, comprising:

a first filter having a sharp interpolation characteristic, the first filter interpolating a selected image position in the image to generate a sharp interpolation output value;

a second filter having a smooth interpolation characteristic, the second filter interpolating the selected image position in the image to generate a smooth interpolation output value;

each of the polyphase filters comprises a N -tap M phase polyphase filter;

a controller that calculates a weighting coefficient for the output of each filter by estimating the image high frequency level at the selected image position, and calculating a weighting coefficient for the output of the filter based on the estimated image high frequency level such that the image high frequency level at the selected image position is estimated based on image high frequency components measured using a high-pass filtering process at original image pixels neighboring the selected image position; and

a combiner that selectively combines the output values from the filters as a function of the weighting coefficients, to generate an interpolation output value for the selected image position of an interpolated output image;

_____ wherein the image high frequency component ϕ_i at each of the original image pixels is measured according to the relation:

$$\phi_i = |p_i - 0.5 * (p_{i-1} + p_{i+1})|$$

wherein p_i is original image pixel value where image high frequency component is to be measured, and p_{i-1} and p_{i+1} are values of its neighboring pixels.

36. (Original) The system of claim 35, wherein the image high frequency level φ at the selected image position is estimated according to the relation:

$$\varphi = \sum_{i=-\frac{N}{2}+1}^{\frac{N}{2}} (0.5 * (f_{-i+1}^j + g_{-i+1}^j) * \phi_i)$$

wherein ϕ_i , $i = -\frac{N}{2} + 1, \dots, 0, \dots, \frac{N}{2}$ are the image high frequency components calculated at the original image pixels that are within the filtering range of interpolation to the selected image position, f_i^j and g_i^j are filter coefficients of sub-filters f^j and g^j for the first filter and the second filter, respectively, and j is the interpolation phase for the selected image position.

37. (Original) The system of claim 32, wherein the image high frequency level at the selected image position is estimated based on the image high frequency components calculated at two original image pixels closest to the selected image position.

38. (Currently amended) ~~The system of claim 37,~~ An interpolation system that interpolates image positions in an original image to produce an interpolated output image, wherein the original image is represented by digital input pixel data, comprising:

_____ a first filter having a sharp interpolation characteristic, the first filter interpolating a selected image position in the image to generate a sharp interpolation output value;

_____ a second filter having a smooth interpolation characteristic, the second filter interpolating the selected image position in the image to generate a smooth interpolation output value;

each of the polyphase filters comprises a N -tap M phase polyphase filter;

_____ a controller that calculates a weighting coefficient for the output of each filter by estimating the image high frequency level at the selected image position, and calculating a weighting coefficient for the output of the filter based on the estimated image high frequency level such that the image high frequency level at the selected image position is estimated based on image high frequency components measured at original image pixels closest to the selected image position;

_____ a combiner that selectively combines the output values from the filters as a function of the weighting coefficients, to generate an interpolation output value for the selected image position of an interpolated output image;

_____ wherein the image high frequency level φ at the selected image position is estimated according to the relation:

$$\varphi = d_1 * \phi_0 + d_0 * \phi_1$$

wherein ϕ_0 and ϕ_1 are the image high frequency components calculated at the two closest original image pixels, d_0 and d_1 are the distances between the selected interpolation position and the two closest original image pixels, the distance between two neighboring original image pixels is assumed to be 1, such that $d_0 + d_1 = 1$.

39. (Original) The system of claim 32, wherein the image high frequency level at the selected image position is estimated based on the image high frequency component measured at original image pixels that are within the filtering range of interpolation to the selected image position.

40. (Currently amended) ~~The system of claim 39,~~ An interpolation system that interpolates image positions in an original image to produce an interpolated output image, wherein the original image is represented by digital input pixel data, comprising:

_____ a first filter having a sharp interpolation characteristic, the first filter interpolating a selected image position in the image to generate a sharp interpolation output value;

_____ a second filter having a smooth interpolation characteristic, the second filter interpolating the selected image position in the image to generate a smooth interpolation output value;

each of the polyphase filters comprises a N -tap M phase polyphase filter;

a controller that calculates a weighting coefficient for the output of each filter by estimating the image high frequency level at the selected image position, and calculating a weighting coefficient for the output of the filter based on the estimated image high frequency level such that the image high frequency level at the selected image position is estimated based on image high frequency components measured at original image pixels neighboring the selected image position;

a combiner that selectively combines the output values from the filters as a function of the weighting coefficients, to generate an interpolation output value for the selected image position of an interpolated output image;

_____ wherein the image high frequency level ϕ at the selected image position is estimated according to the relation:

$$\phi = \sum_{i=-\frac{N}{2}+1}^{\frac{N}{2}} (0.5 * (f_{-i+1}^j + g_{-i+1}^j) * \phi_i)$$

wherein ϕ_i , $i = -\frac{N}{2} + 1, \dots, 0, \dots, \frac{N}{2}$ are the image high frequency

components calculated at the original image pixels that are within the filtering range of interpolation to the selected image position, f_i^j and g_i^j are the filter coefficients of sub-filters f^j and g^j for the first filter and the second filter, respectively, and j is the interpolation phase for the selected image position.